

<b>Model Name</b>	<b>SE-3200</b>
<b>Product Name</b>	<b>HD 12-Channel Digital Video Switcher</b>
<b>Video Standard</b>	Full HD
<b>Video Format</b>	1080p 50/59.94/60Hz, 1080i 50/59.94/60Hz, 720p 50/59.94/60Hz,
<b>Video Processing</b>	SDI: 4:2:2 HDMI: YUV 4:2:2, RGB: 4:4:4
<b>Input Routable / Crosspoint</b>	All 12, repeatable
<b>Video Input</b>	8x SDI, 4x HDMI
<b>Mix HD &amp; SD Source</b>	N/A
<b>Computer Graphic Interface</b>	4 via HDMI
<b>Video Output</b>	6x SDI Outputs Assignable: PGM, PVW, PGM Clean & Multi-View, Input 1-12 3x HDMI Assignable: PGM & Multi-View
<b>Down-converted output</b>	N/A
<b>Built-In Multi-View Monitoring Out</b>	HDMI
<b>Audio Input</b>	4x Balanced XLR
<b>Audio Output</b>	2x Balanced XLR
<b>Embedded Audio Support</b>	Embedded 4-CH Audio Output
<b>Audio Delay Calibration</b>	up to 16 Fields or 8 Frames per Channel
<b>A+V Switching</b>	Yes
<b>Chromakey</b>	4
<b>USK</b>	4x USK support Chromakey & Linear/ Luma Key
<b>DSK</b>	2x DSK support Lumakey & Linear key (Key / Fill)
<b>Picture in Picture</b>	8 (4x PIP, 4x Flex Source)
<b>Logo Insertion</b>	2
<b>Still Store</b>	500
<b>Effects</b>	DVE, FTB, Cut, 32 Wipe with border

<b>Transition Preview</b>	<b>Full Transitions Preview</b>
<b>Sync / Reference In/Out</b>	Built-in Genlock Support external sync with loop thru
<b>Tally Output</b>	1x D-sub 25pin, Dual Color
<b>PC Remote Control</b>	Via Ethernet (free Window software) or RS-422 / RS-232
<b>Built-in Audio Mixer</b>	N/A
<b>Special Features</b>	4 User Memory Preset Free Virtual Set and Stinger Transition included
<b>Chassis</b>	2 units, 2RU Rack-Mount Mainframe
<b>Power</b>	DC 12V 69W
<b>Accessory</b>	CB-60/61/62 (30/50/100m)